

TOMAR

Instruction Manual

200-6

Low Profile LED Lightstick Series
for External Flasher Control

IS0483-01
10.30.2007

TOMAR Electronics, Inc.
2100 W. Obispo Ave.
Gilbert, AZ 85233 USA

800.338.3133 ph
800.688.6627 fax

www.tomar.com

Wires

RED	+12VDC
RED/BLK	+12VDC
ORG/BLK	+12VDC
BLACK	Lamp # 1 (PF3) - GROUND to activate
GREEN	Lamp # 2 (PF2) - GROUND to activate
WHITE	Lamp # 3 (PF1) - GROUND to activate
BLUE	Lamp # 4 (DF1) - GROUND to activate
BLK/WHT	Lamp # 5 (DF2) - GROUND to activate
WHT/BLK	Lamp # 6 (DF3) - GROUND to activate

Electrical

Input Voltage 12VDC thru 28VDC

Complete installation with wire rated for 125% of amperage draw.

5 Amp in-line fuse recommended per module.

WARNING: DO NOT SEAL TOMAR LED LAMPS OR SEAL THE LED LAMP TO THE VEHICLE MOUNTING SURFACE! DOING SO WILL PREVENT WATER DRAINAGE AND VOID THE LAMP WARRANTY.

Current Draw Per Module - in Steady Burn Mode @ 12VDC

High Power Model	1.6 Amps Average
Standard Power Model	1.2 Amps Average
Low Current Model	0.8 Amps Average

