

930NH-6407 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

	DF3	DF2	DF1	FC	PF1	PF2	PF3
DC							PC
DA							PA
	DR3	DR2	DR1	RC	PR1	PR2	PR3

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION	
		REAR / ALLEY STROBES & HALOGENS	FRONT / CORNER STROBES & HALOGENS
0	NONE	NONE	NONE
1	ORG	<p style="text-align: center;"><u>STROBES</u></p> DR1 ALTERNATES WITH PR1 (4 PULSES PER BURST)	<p style="text-align: center;"><u>STROBES</u></p> DF1 ALTERNATES WITH PF1 (4 PULSES PER BURST)
		<p style="text-align: center;"><u>HALOGENS</u></p> DR2 ALTERNATES WITH PR2	
2	ORG & BLU	<p style="text-align: center;"><u>STROBES</u></p> DR3, PR3 & DA SIMULTANEOUS AND ALTERNATE WITH DR1, PR1 & PA SIMULTANEOUS (6 PULSES PER BURST)	<p style="text-align: center;"><u>STROBES</u></p> DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF1 & PF1 SIMULTANEOUS (6 PULSES PER BURST)
		<p style="text-align: center;"><u>HALOGENS</u></p> DR2 ALTERNATES WITH PR2	<p style="text-align: center;"><u>HALOGENS</u></p> DF2 ALTERNATES WITH PF2
3	ORG & BLU & WHT/BLK	<p style="text-align: center;"><u>STROBES</u></p> DR3, PR3 & DA SIMULTANEOUS AND ALTERNATE WITH DR1, PR1 & PA SIMULTANEOUS (6 PULSES PER BURST)	<p style="text-align: center;"><u>STROBES</u></p> DF3 & PF3 SIMULTANEOUS AND ALTERNATE WITH DF1 & PF1 SIMULTANEOUS (6 PULSES PER BURST)
		<p style="text-align: center;"><u>HALOGENS</u></p> DR2 ALTERNATES WITH PR2	<p style="text-align: center;"><u>HALOGENS</u></p> DF2 ALTERNATES WITH PF2 DC ALTERNATES WITH PC

CONTROL WIRES FOR OPTIONAL HALOGENS

CONTROL WIRE ACTIVATED

RED/WHITE
BROWN
GRAY
YELLOW

HALOGEN LAMP

RC (REAR WORK)
FC (TAKEDOWN)
DA (DRIVER ALLEY)
PA (PASSENGER ALLEY)

**NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.**