465N-8009 FLASH PATTERN

LIGHTBAR LAMP CONFIGURATION

DF4 DF3 DF2 DF1 FC PF1 PF2 PF3 PF4
DC PC

MODE	CONTROL WIRES ACTIVATED	LAMP OPERATION FRONT / CORNER STROBES
1	ORG	DF1 ALTERNATES WITH PF1 (4 PULSES PER BURST)
2	ORG & BLU	DF4 & PF4 SIMULTANEOUS AND ALTERNATE WITH DF3 & PF3 SIMULTANEOUS (6 PULSES PER BURST) PF1, DF1 & (*FCL) SIMULTANEOUS AND ALTERNATE WITH DF2, PF2 & (*FCR) SIMUTANEOUS (6 PULSES PER BURST)
3	ORG & WHT/BLK	DF4 & PF4 SIMULTANEOUS AND ALTERNATE WITH DF3 & PF3 SIMULTANEOUS (6 PULSES PER BURST) PF1, DF1 & (*FCL) SIMULTANEOUS AND ALTERNATE WITH DF2, PF2 & (*FCR) SIMUTANEOUS (6 PULSES PER BURST) DC ALTERNATES WITH PC (3 PULSES PER BURST)
4	ORG & BLU & WHT/BLK (**OPTIONAL PREEMPTION**)	SAME AS MODE 3 NOTE: EXCEPT LAMPS DF4, DF3, PF3 & PF4 EMITS A **PREEMPTION** SIGNAL

* **NOTE**: FCL & FCR ARE OPTIONAL DUAL STROBES IN THE FC LOCATION..

CONTROL WIRES FOR OPTIONAL HALOGEN

CONTROL WIRE ACTIVATED	**HALOGEN LAMP**	
RED/WHT	FC	TAKEDOWN or FRONT FLASHER
GRY	DF1 or DF2	SPLIT TAKEDOWN
YEL	PF1 or PF2	SPLIT TAKEDOWN

CONTROL WIRES FOR OPTIONAL PREEMPTION

CONTROL WIRE ACTIVATED	**DEACTIVATE PRE EMISSION**
BRN	PARKING BRAKE OVERRIDE

CONTROL WIRES FOR OPTIONAL PRE2-1C

CONTROL WIRE ACTIVATED	**FC STROBE LAMP**
BRN	ACTIVATE PREEMPTION EMITTER

CONTROL WIRES FOR OPTIONAL ICC MARKER LIGHTS

CONTROL WIRE ACTIVATED	
BRN/WHT	ACTIVATE ICC MARKER LIGHTS

NOTE: GREEN control wire activates high intensity to strobes.
Apply +12vdc to appropriate control wire to activate desired function.